## ELECTRA SW 1000 Be

## Product specification sheet

750W BASH® amplifier. Very high power and current output.

Built-in DSP (Digital Signal Processor). High setting accuracy. Digital serial connection for several subwoofers.

Body in metallic Slate Grey piano lacquer. Panels in wood veneering, varnish 11 coats.



\_\_ LCD screen. Remote sensor.

13" (33cm) "W" cone subwoofer.
Patented composite sandwich.
Outstanding stiffness and lightness.

Front laminar port.

No noise, no distortion.

No dynamic compression.

Spikes and plastic feet supplied.







- •100% Focal loudspeakers and drive-units made in France
- ◆ Standard finishes, on demand or special personalized finishes
- ◆ High size/performance ratio for optimum integration
- ◆ Exclusive Focal technologies

	Classic	Signature	
Side panel Standard			
Side panel On demand			
	Zebrano	Macassar	Slate Grey

Туре	Active vented subwoofer	
Drivers	13" (33cm) "W" woofer	
Frequency response (+/-3dB)	20Hz - 150Hz	
Low frequency point (-6dB)	18Hz	
Subwoofer features	Adjustable LPF: 50Hz to 150Hz (24dB/oct.), 48dB/oct. adjustable subsonic filter, adjustable phase, Boost mode, Night mode, 3 user memories, LFe/Stereo/Digital inputs.	
Recommended amplifier power	600W (750W max.) BASH® amplifier	
Dimensions (HxWxD)	21 <sup>1/16</sup> x19 <sup>11/16</sup> x17" (535x500x432mm)	
Net weight	92.4lbs (42kg)	

24 bit digital processor, possibility of settings and adaptation to the room dynamics and dimensions, 600 Watt RMS BASH® amplifier mated to a 13" [33cm] "W" cone, the **SW 1000** Be offers high level reproduction with a low roll-off at 18Hz and a sound pressure level achieving 119dB.





